



Outstanding Model Gear

OMG-MT-AURORA
AURORA

SENSORED BRUSHLESS TOP MOTOR
For 1/27 1/28 Mini-Z RC Car

Rotor Poles:2

Max Voltage: <8.4V

Power:80W

Max RPM:60000

Motor Size:Φ15×25mm

Shaft Diameter(mm):Φ2

Weight:17g

Length of extend shaft:10mm

KV (RPM/Volt)	Max amps(A)	No-load current(A)	Resistance (Ω)
3500	8	0.25	0.74
4500	9	0.35	0.45
5500	10	0.50	0.28



RC OMG



rcomg-zf



Rcomg CoCo



rcomg



MOTOR

SENSORED BRUSHLESS TOP MOTOR
For 1/27 1/28 Mini-Z RC Car

Rotor Poles:2

Max Voltage:<8.4V

Power:80W


Max RPM:60000

Motor Size:Φ15×25mm

Shaft Diameter(mm):Φ2

Weight:17g

Length of extend shaft:10mm



KV (RPM/Volt)	Max amps(A)	No-load current(A)	Resistance (Ω)
3500	8	0.25	0.74
4500	9	0.35	0.45
5500	10	0.50	0.28



RoHS

MADE IN CHINA